

Q33DAPA

Quad 33 Disc Adaptor type A

Modifications to the Quad 33 disc adaptor board to provide an input of $47k\Omega$ in parallel with $330pF$ (to which a normal pickup lead will add between 120 and $220pF$) with an input sensitivity of $3.8mV$, to suit the Shure V15/III and similar cartridges.

1. Remove R101, 102, 105, 106, 107 and 108.
2. Insert R101 $47k\Omega$ in parallel with $330pF$ (150pF with SME
" R102 $47k\Omega$ in parallel with $330pF$ (3009 Mk.III arm
" R105 220Ω
" R106 220Ω
" R107 470Ω
" R108 470Ω

The M2 position is unaltered and may thus be used with other cartridges in the normal way.